

HP 620/50/B12 P28

Spannung: 50 V

nl=3511.2U/min
ns=72.5U/min/VIo=4.8A
kn=-24.34U/min/A

kM=17.63Ncm/A

Spannung [V]	Strom [A]	Drehzahl [U/min]	Pin [W]	Pout [W]	Drehmoment [Ncm]	Wirkungsgrad [%]
50.0	10.0	3420.1	499.9	329.0	91.9	65.81
50.0	11.0	3390.3	549.9	388.7	109.5	70.69
50.0	12.0	3360.9	599.9	447.4	127.1	74.58
50.0	13.0	3331.7	649.8	505.0	144.7	77.72
50.0	14.0	3302.8	699.8	561.6	162.4	80.26
50.0	15.0	3274.2	749.7	617.2	180.0	82.32
50.0	16.0	3245.9	799.6	671.7	197.6	84.00
50.0	17.0	3217.8	849.6	725.3	215.2	85.37
50.0	18.0	3190.0	899.5	777.9	232.9	86.49
50.0	19.0	3162.5	949.4	829.6	250.5	87.38
50.0	20.0	3135.3	999.3	880.3	268.1	88.09
50.0	21.0	3108.3	1049.3	930.1	285.8	88.65
50.0	22.0	3081.7	1099.2	979.0	303.4	89.07
50.0	23.0	3055.3	1149.1	1027.1	321.0	89.38
50.0	24.0	3029.2	1199.0	1074.2	338.6	89.59
50.0	25.0	3003.3	1248.9	1120.5	356.3	89.72
50.0	26.0	2977.7	1298.7	1165.9	373.9	89.77
49.9	27.0	2952.5	1348.6	1210.5	391.5	89.76
49.9	28.0	2927.5	1398.5	1254.3	409.1	89.69
49.9	29.0	2902.7	1448.4	1297.2	426.8	89.57
49.9	30.0	2878.3	1498.2	1339.4	444.4	89.40
49.9	31.0	2854.1	1548.1	1380.9	462.0	89.20
49.9	32.0	2830.2	1598.0	1421.6	479.6	88.96
49.9	33.0	2806.6	1647.8	1461.5	497.3	88.69
49.9	34.0	2783.2	1697.6	1500.7	514.9	88.40
49.9	35.0	2760.2	1747.5	1539.2	532.5	88.08
49.9	36.0	2737.4	1797.3	1577.0	550.1	87.74
49.9	37.0	2714.9	1847.2	1614.2	567.8	87.39
49.9	38.0	2692.6	1897.0	1650.7	585.4	87.02
49.9	39.0	2670.7	1946.8	1686.5	603.0	86.63
49.9	40.0	2649.0	1996.6	1721.7	620.7	86.23
49.9	41.0	2627.6	2046.4	1756.3	638.3	85.82
49.9	42.0	2606.5	2096.2	1790.3	655.9	85.41
49.9	43.0	2585.6	2146.0	1823.7	673.5	84.98
49.9	44.0	2565.1	2195.8	1856.5	691.2	84.55
49.9	45.0	2544.8	2245.6	1888.8	708.8	84.11
49.9	46.0	2524.8	2295.4	1920.6	726.4	83.67
49.9	47.0	2505.0	2345.2	1951.8	744.0	83.23
49.9	48.0	2485.6	2394.9	1982.5	761.7	82.78
49.9	49.0	2466.4	2444.7	2012.7	779.3	82.33
49.9	50.0	2447.5	2494.5	2042.5	796.9	81.88