

HP 620/50/B12 P28

Spannung: 55 V

nl=3863.6U/min
ns=72.7U/min/VIo=4.9A
kn=-26.48U/min/A

kM=17.64Ncm/A

Spannung [V]	Strom [A]	Drehzahl [U/min]	Pin [W]	Pout [W]	Drehmoment [Ncm]	Wirkungsgrad [%]
54.9	10.0	3763.6	549.0	353.6	89.7	64.41
54.9	11.0	3731.8	603.9	419.6	107.4	69.47
54.9	12.0	3700.4	658.8	484.4	125.0	73.52
54.9	13.0	3669.2	713.7	548.1	142.6	76.79
54.9	14.0	3638.2	768.6	610.6	160.3	79.44
54.9	15.0	3607.6	823.5	672.1	177.9	81.61
54.9	16.0	3577.2	878.4	732.5	195.5	83.39
54.9	17.0	3547.1	933.3	791.9	213.2	84.84
54.9	18.0	3517.2	988.2	850.2	230.8	86.03
54.9	19.0	3487.7	1043.1	907.4	248.5	86.99
54.9	20.0	3458.4	1098.0	963.7	266.1	87.76
54.9	21.0	3429.3	1152.9	1018.9	283.7	88.38
54.9	22.0	3400.6	1207.8	1073.2	301.4	88.85
54.9	23.0	3372.1	1262.7	1126.4	319.0	89.21
54.9	24.0	3343.8	1317.6	1178.8	336.6	89.46
54.9	25.0	3315.9	1372.5	1230.2	354.3	89.63
54.9	26.0	3288.2	1427.4	1280.6	371.9	89.72
54.9	27.0	3260.8	1482.3	1330.2	389.5	89.74
54.9	28.0	3233.6	1537.2	1378.8	407.2	89.70
54.9	29.0	3206.8	1592.0	1426.6	424.8	89.61
54.9	30.0	3180.2	1646.9	1473.5	442.5	89.47
54.9	31.0	3153.8	1701.8	1519.5	460.1	89.29
54.9	32.0	3127.8	1756.7	1564.7	477.7	89.07
54.9	33.0	3102.0	1811.6	1609.1	495.4	88.82
54.9	34.0	3076.5	1866.5	1652.7	513.0	88.55
54.9	35.0	3051.2	1921.4	1695.5	530.6	88.24
54.9	36.0	3026.2	1976.2	1737.5	548.3	87.92
54.9	37.0	3001.5	2031.1	1778.7	565.9	87.57
54.9	38.0	2977.1	2086.0	1819.2	583.5	87.21
54.9	39.0	2952.9	2140.9	1859.0	601.2	86.83
54.9	40.0	2929.0	2195.8	1898.1	618.8	86.44
54.9	41.0	2905.4	2250.6	1936.4	636.4	86.04
54.9	42.0	2882.0	2305.5	1974.1	654.1	85.62
54.9	43.0	2858.9	2360.4	2011.1	671.7	85.20
54.9	44.0	2836.1	2415.3	2047.4	689.4	84.77
54.9	45.0	2813.6	2470.2	2083.1	707.0	84.33
54.9	46.0	2791.3	2525.0	2118.1	724.6	83.89
54.9	47.0	2769.3	2579.9	2152.6	742.3	83.44
54.9	48.0	2747.6	2634.8	2186.4	759.9	82.98
54.9	49.0	2726.1	2689.7	2219.7	777.5	82.53
54.9	50.0	2704.9	2744.5	2252.4	795.2	82.07